


PAM8301AAF Datasheet



https://www.DiGi-Electronics.com

DiGi Electronics Part Number PAM8301AAF-DG

Manufacturer Diodes Incorporated

Manufacturer Product Number PAM8301AAF

Description IC AMP CLASS D MONO 1.5W SOT23-6

Detailed Description Amplifier IC 1-Channel (Mono) Class D SOT-23-6



Tel: +00 852-30501935

RFQ Email: Info@DiGi-Electronics.com

DiGi is a global authorized distributor of electronic components.



8542.33.0001

Purchase and inquiry

Manufacturer Product Number:	Manufacturer:
PAM8301AAF	Diodes Incorporated
Series:	Product Status:
	Not For New Designs
Type:	Output Type:
Class D	1-Channel (Mono)
Max Output Power x Channels @ Load:	Voltage - Supply:
1.5W x 1 @ 80hm	2.5V ~ 5.5V
Features:	Mounting Type:
Depop, Short-Circuit and Thermal Protection	Surface Mount
Operating Temperature:	Supplier Device Package:
-40°C ~ 85°C (TA)	SOT-23-6
Package / Case:	Base Product Number:
SOT-23-6	PAM8301

Environmental & Export classification

RoHS Status:	Moisture Sensitivity Level (MSL):
ROHS3 Compliant	3 (168 Hours)
REACH Status:	ECCN:
REACH Unaffected	EAR99
HTSUS:	



NOT RECOMMENDED FOR NEW DESIGN USE PAM8013 or PAM8304

PAM8301

FILTERLESS CLASS-D MONO AUDIO AMPLIFIER

Description

The PAM8301 is a 1.5W Class-D mono audio amplifier. Its low THD+N feature offers high quality sound reproduction. The new filterless architecture allows the device to drive speaker directly instead of using low-pass output filters, therefore saving system cost and PCB area.


With the same number of external components, the efficiency of the PAM8301 is much better than that of Class-AB cousins. It can optimize battery life thus is ideal for portable applications.

The PAM8301 is available in SOT23-6 package.

Features

- 1.5W Output at 10% THD with a 8Ω Load and 5V Power Supply
- Filterless, Low Quiescent Current and Low EMI
- High Efficiency up to 88%
- Superior Low Noise
- Short Circuit Protection
- Thermal Shutdown
- Few External Components to Save Space and Cost
- Tiny SOT23-6 Package
- Pb-Free Package


Pin Assignments



Applications

- PMP/MP4
- GPS
- Portable Speakers
- Walkie Talkie
- Handsfree Phones/Speaker Phones
 - Cellular Phones

Typical Applications Circuit






Pin Descriptions

Pin	Pin	Function	
Number	Name	Function	
1	OUT-	Negative Output	
2	GND	Ground	
3	IN	Input	
4	SD	Shutdown, Active Low	
5	VDD	Power Supply	
6	OUT+	Positive Output	

Functional Block Diagram



Absolute Maximum Ratings (@T_A = +25°C, unless otherwise specified.)

These are stress ratings only and functional operation is not implied. Exposure to absolute maximum ratings for prolonged time periods may affect device reliability. All voltages are with respect to ground.

Parameter	Rating	Unit
Supply Voltage at No Input Signal	6.0	V
Input Voltage Range	-0.3 to V _{DD} +0.3	V
Maximum Junction Temperature	150	
Storage Temperature	-65 to +150	°C
Soldering Temperature	300, 5sec	

Recommended Operating Conditions (@TA = +25°C, unless otherwise specified.)

Parameter	Rating	Unit
Supply Voltage Range	2.5 to 5.5	V
Operation Temperature Range	-40 to +85	°C
Junction Temperature Range	-40 to +125	°C



Thermal Information


Parameter	Package	Symbol	Max	Unit
Thermal Resistance (Junction to Ambient)	SOT23-6	θ_{JA}	250	°C/W
Thermal Resistance (Junction to Case)	SOT23-6	θ_{JC}	130	C/VV

Electrical Characteristics (@ $T_A = +25^{\circ}C$, $V_{DD} = 5V$, Gain = 24dB, $R_L = 8\Omega$, unless otherwise specified.)

Symbol	Parameter	Test Conditions			Тур	Max	Units
V_{DD}	Supply Voltage Range			2.5		5.5	V
IQ	Quiescent Current	No Load			4	8	mA
I _{SHDN}	Shutdown Current	V _{SHDN} = 0V				1	μΑ
V _{SH}	SHDN Input High			1.2			V
V _{SL}	SHDN Input Low		V / \			0.4	V
D	Drain-Source On-State Resistance	I 100mΛ	P MOSFET		0.45		Ω
R _{DS(ON)}	Diani-Source Oil-State Resistance	I _{DS} = 100mA	N MOSFET		0.20		12
Po	Output Power	f = 1kHz	THD+N = 1%		1.2		W
10	Output i owei	1 - 11(1)2	THD+N = 10%		1.5		VV
THD+N	D+N Total Harmonic Distortion Plus Noise $R_L = 8\Omega$, $P_O = 200$ mW			0.2		%	
IIIDTN	Total Halffloriic Distortion Flus Noise	$R_L = 8\Omega$, $P_0 = 0.5W$			0.3		70
PSRR	AC Power Supply Ripple Rejection	No Inputs, f = 1kHz, V _{PP} = 200mV			50		dB
G _V	Gain				24		dB
\/	Output Naige	No A-Weighting			180		\/
V _N	Output Noise	A-Weighting			120		μV
fosc	Oscillator Frequency			200	250	300	kHz
η	Peak Efficiency	f = 1kHz		85	88		%
SNR	Signal to Noise Ratio	f = 20 to 20kHz			78		dB
OTP	Over Temperature Protection				135		°C
OTH	Over Temperature Hysterisis				30		°C




Typical Performance Characteristics (@T_A = +25°C, unless otherwise specified.)







Typical Performance Characteristics (cont.) (@TA = +25°C, unless otherwise specified.)






Typical Performance Characteristics (cont.) (@T_A = +25°C, unless otherwise specified.)





Application Information

Test Setup for Performance Testing



Notes:

- 1. The AP AUX-0025 low pass filter is necessary for every class-D amplifier measurement with AP analyzer.
- 2. Two 22µH inductors are used in series with load resistor to emulate the small speaker for efficiency measurement.



Application Information (cont.)

Maximum Gain

As shown in block diagram (Page 2), the PAM8301 has two internal amplifier stages. The first stage's gain is externally configurable, while the second stage's is internally fixed. The closed-loop gain of the first stage is set by selecting the ratio of RF to RI while the second stage's gain is fixed at 2x. The output of amplifier one serves as the input to amplifier two, thus the two amplifiers produce signals identical in magnitude, but different in phase by +180°. Consequently, the differential gain for the IC is

$$A_{VD} = 20*log [2*(R_F/R_I)]$$

The PAM8301 sets maximum $R_F = 80k\Omega$, minimum $R_I = 10k\Omega$, so the maximum closed-gain is 24dB.

Input Capacitors (C_I)

In typical application, an input capacitor, CI, is required to allow the amplifier to bias input signals to a proper DC level for optimum operation. In this case, CI and the minimum input impedance RI (10k internal) form a high pass filter with a corner frequency determined by the following equation:

$$f_C = \frac{1}{2\Pi R_I C_I}$$

It is important to choose the value of CI as it directly affects low frequency performance of the circuit, for example, when an application requires a flat bass response as low as 100Hz. Equation is reconfigured as follows:

$$C_{l} = \frac{1}{2\Pi R_{l} f_{l}}$$

As the input resistance is variable, for the C_I value of $0.16\mu F$, one should actually choose the C_I within the range of $0.1\mu F$ to $0.22\mu F$. A further consideration for this capacitor is the leakage path from the input source through the input network (R_I, R_F, C_I) to the load. This leakage current creates a DC offset voltage at the input to the amplifier that reduces useful headroom, especially in high gain application. For this reason, a low leakage tantalum or ceramic capacitor is the best choice. When a polarized capacitor is used, the positive side of the capacitor should face the amplifier input in most applications as the DC level is held at $V_{DD}/2$, which is likely higher than the source DC level. Please note that it is important to confirm the capacitor polarity in the application.

Power Supply Decoupling (Cs)

The PAM8301 is a high-performance CMOS audio amplifier that requires adequate power supply decoupling to ensure the output THD and PSRR as low as possible. Power supply decoupling affects low frequency response. Optimum decoupling is achieved by using two capacitors of different types that target different types of noise on the power supply leads. For higher frequency transients, spikes, or digital hash on the line, a good low equivalent-series-resistance (ESR) ceramic capacitor, typically $1.0\mu F$ is good, placing it as close as possible to the device V_{DD} terminal. For filtering lower-frequency noise signals, a capacitor of $10\mu F$ or larger, closely located to near the audio power amplifier is recommended.

Shutdown Operation

In order to reduce shutdown power consumption, the PAM8301 contains shutdown circuitry for turn off the amplifier. This shutdown feature turns the amplifier off when a logic low is applied on the SHDOWN pin. By switching the shutdown pin over to GND, the PAM8301 supply current draw will be minimized in idle mode.

For the best power on/off pop performance, the amplifier should be set in the shutdown mode prior to power on/off operation.

Under Voltage Lock-Out (UVLO)

The PAM8301 incorporates circuitry to detect low on or off voltage. When the supply voltage drops to 2.1V or below, the PAM8301 goes into a state of shutdown, and the device comes out of its shutdown state and starts to normal operation by reset the power supply or SD pin.



Application Information (cont.)

How to Reduce EMI (Electro Magnetic Interference)

A simple solution is to put an additional capacitor $1000\mu F$ at power supply terminal for power line coupling if the traces from amplifier to speakers are short (< 20cm).

Most applications require a ferrite bead filter as shown at Figure 1. The ferrite filter depresses EMI of around 1MHz and higher. When selecting a ferrite bead, choose one with high impedance at high frequencies and low impedance at low frequencies.





Figure 1: Ferrite Bead Filter to Reduce EMI


Ordering Information



Part Number Part Marking		Package Type	Standard Package	
PAM8301AAF	FPXYW	SOT23-6	3000 Unit/Tape&Reel	



Marking Information




FP: Product Code of PAM8301

X: Internal Code

Y: Year W: Week

Package Outline Dimensions (All dimensions in mm.)

SOT23-6





Symbol	А	A1	A2	b	С	D	E
Spec	1.20±0.25	0.10±0.05	1.10±0.2	0.40±0.1	0.15±0.07	2.90±0.1	2.80±0.2
Symbol	E1	е	e 1	L	L1	θ	
Spec	1.60±0.1	0.95BSC	1.90BSC	0.55±0.25	0.60REF	4°±4°	

Unit: Millimeter



IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2020, Diodes Incorporated

www.diodes.com

PAM8301 Document number: DS36431 Rev. 2 - 3 10 of 10 www.diodes.com



OUR CERTIFICATE

DiGi provide top-quality products and perfect service for customer worldwide through standardization, technological innovation and continuous improvement. DiGi through third-party certification, we striciy control the quality of products and services. Welcome your RFQ to Email: Info@DiGi-Electronics.com

















Tel: +00 852-30501935

RFQ Email: Info@DiGi-Electronics.com