

ER15M121JP Datasheet



<https://www.DiGi-Electronics.com>

DiGi Electronics Part Number	ER15M121JP-DG
Manufacturer	Gowanda Electronics
Manufacturer Product Number	ER15M121JP
Description	M39010 LEV-R AXIAL INDUCTOR
Detailed Description	1.2 μ H Unshielded Molded Inductor 650 mA 420mOhm Max Axial



Tel: +00 852-30501935

RFQ Email: Info@DiGi-Electronics.com

DiGi is a global authorized distributor of electronic components.

Purchase and inquiry

Manufacturer Product Number:

ER15M121JP

Series:

ER15M

Type:

Molded

Inductance:

1.2 μ H

Current Rating (Amps):

650 mA

Shielding:

Unshielded

Q @ Freq:

33 @ 7.9MHz

Ratings:

-

Inductance Frequency - Test:

7.9 MHz

Mounting Type:

Through Hole

Supplier Device Package:

Axial

Height - Seated (Max):

-

Manufacturer:

Gowanda Electronics

Product Status:

Active

Material - Core:

Phenolic

Tolerance:

\pm 5%

Current - Saturation (Isat):

-

DC Resistance (DCR):

420mOhm Max

Frequency - Self Resonant:

180MHz

Operating Temperature:

-55°C ~ 125°C

Features:

-

Package / Case:

Axial

Size / Dimension:

0.156" Dia x 0.375" L (3.96mm x 9.52mm)

Environmental & Export classification

RoHS Status:

Not applicable

REACH Status:

REACH Unaffected

HTSUS:

8504.50.8000

Moisture Sensitivity Level (MSL):

1 (Unlimited)

ECCN:

EAR99

OUR CERTIFICATE

DiGi provide top-quality products and perfect service for customer worldwide through standardization, technological innovation and continuous improvement. DiGi through third-party certification, we stricly control the quality of products and services. Welcome your RFQ to

Email: Info@DiGi-Electronics.com



Tel: +00 852-30501935

RFQ Email: Info@DiGi-Electronics.com

DiGi is a global authorized distributor of electronic components.