

## **ER17S563JM Datasheet**



DiGi Electronics Part Number ER17S563JM-DG

Manufacturer Gowanda Electronics

Manufacturer Product Number ER17S563JM

Description M39010 LEV-R AXIAL INDUCTOR

Detailed Description 560 µH Shielded Molded Inductor 90 mA 10.50hm

Max Axial

https://www.DiGi-Electronics.com



Tel: +00 852-30501935

RFQ Email: Info@DiGi-Electronics.com

DiGi is a global authorized distributor of electronic components.



## **Purchase and inquiry**

Manufacturer Product Number:	Manufacturer:
ER17S563JM	Gowanda Electronics
Series:	Product Status:
ER17S	Active
Type:	Material - Core:
Molded	Ferrite
Inductance:	Tolerance:
560 μΗ	±5%
Current Rating (Amps):	Current - Saturation (Isat):
90 mA	
Shielding:	DC Resistance (DCR):
Shielded	10.50hm Max
Q @ Freq:	Frequency - Self Resonant:
60 @ 790kHz	4.7MHz
Ratings:	Operating Temperature:
	-55°C ~ 125°C
Inductance Frequency - Test:	Features:
790 kHz	
Mounting Type:	Package / Case:
Through Hole	Axial
Supplier Device Package:	Size / Dimension:
Axial	0.162" Dia x 0.410" L (4.11mm x 10.41mm)
Height - Seated (Max):	

## **Environmental & Export classification**

8504.50.8000

RoHS Status:	Moisture Sensitivity Level (MSL):
Not applicable	1 (Unlimited)
REACH Status:	ECCN:
REACH Unaffected	EAR99
HTSUS:	



## **OUR CERTIFICATE**

DiGi provide top-quality products and perfect service for customer worldwide through standardization, technological innovation and continuous improvement. DiGi through third-party certification, we striciy control the quality of products and services. Welcome your RFQ to Email: Info@DiGi-Electronics.com

















Tel: +00 852-30501935